



Smart Dry Contact Output Module

Product Code:
KASTA-S10IBH

APP Installation

Visit www.kasta.com.au or your app store to download the free KASTA app.
iOS: requires iOS 9.0 or later.
Android: requires Android 4.4 or later.
Devices must support Bluetooth 4.0



Important Safety Information

- This product must be installed by a licensed electrician in accordance with all the requirements of AS/NZS 3000 (current edition) and other relevant Standards and Regulations.
- Electricity MUST be disconnected prior to installation. Failure to do so may result in serious injury and or loss of life.
- Indoor use only. Not suitable for damp or explosive environments.
- Complies to Australian Standards AS/NZS 60950.1:2015, AS/NZS CISPR 15.
- No user serviceable parts inside.

FEATURES

- Mains powered dry contact (voltage free relay) output module.
- ON/OFF control of equipment such as garage doors, motorised gates, sprinkler systems and garden lighting.
- Simple 6 wire connection – A, N, Load, S1, S2, In, Out.
- 4 output modes – 1s, 6s and 9s pulse ON (auto OFF) and toggle ON/OFF (default setting 1s pulse).
- Short Press (or toggle) on input S1 or S2 to activate ON state.
- Can be paired with KASTA remote switches for multi-way control (8x maximum).
- Smart functions via phone/tablet with the app such as schedules, timers, scenes and groups.
- Built in overvoltage protection.
- To prevent a reduction in Bluetooth signal strength, install away from metal objects.

FUNCTION SETUP

S2 CONNECTION

ON/OFF SWITCH	1 CLICK
---------------	---------

Turns connected device on or off.

RESET BUTTON ON MODULE

PAIRING MODE	6 CLICKS
--------------	----------

Enter pairing mode for multi-way control. Lights will pulse.

FACTORY RESET	9 CLICKS
---------------	----------

Restores all settings back to factory.

*If successful, status light will pulse the number of times that the switch was clicked, indicating function.

TECHNICAL SPECIFICATIONS

Operating Temp: -20°C to 40°C

Supply: 220-240V AC 50Hz

Max Load Current: 10A for both voltage range (0-240VAC and 0-30VDC)

CONNECTION DIAGRAM

