

Superb Performance, Built-to-Order

Drawing from years of experience and industry leading technologies like Complex Conic waveguides, TA/TX loudspeakers are designed to meet the needs of today's Installed-AV professionals, with a broad range of systems to provide effective solutions for every sound reinforcement challenge at competitive price points.

The new T Series loudspeakers incorporate the newest generation of Complex Conic horns, with the latest drivers to provide clean, natural sound and tight pattern control. Unlike conventional loud-speaker designs, Complex Conic horns provide consistent beam-width over a wider frequency range, with the natural, transparent sound that Renkus-Heinz is known for.

Made in the USA and fully customizable with the options you've come to expect from Renkus-Heinz including multiple horn dispersions, mounting and mobile options, custom color and weather resistance.

Applications

- The TX/TA81 is a compact, 8" Complex Conic loudspeaker perfect for any application where very small size, consistent directivity and great sonic performance are required.
- Side fill or under balcony applications in House of Worship
- · Foreground music systems
- · High quality distributed sound systems
- Monitoring and fold back applications

Compact Design, Sizable Performance

The TX/TA81 was developed for applications needing consistent directivity and great sonics from a very compact cabinet.

It features a 1.4" voice coil high frequency compression driver with a 1" throat coupled to a Complex Conic horn. The patented Complex Conic horn eliminates high frequency beaming and provides wide angle coverage out to 20 kHz and beyond. The high-efficiency 8" woofer produces a strong low end. Together these deliver a surprisingly high 123 dB peak output level from 90 Hz to 20 kHz.

Designed In Flexibility

Twelve M6 Universal Mounting Points and 10 mm u-bracket mounting plates make installation easy and clean. The Complex Conic horn is field rotatable allowing the installer the flexibility of installing the loudspeaker either vertically or horizontally while maintaining the dispersion necessary for the project.

The TX/TA81 and it's (optional) matching U-Bracket are available in either white or black paint allowing them to bend into most environments.

Available externally powered or with four flavors of built-in amplification; RHAON II networking, monitoring and control, and Dante digital audio, the TX/TA81 brings new levels of versatility to compact loudspeakers.

TA/TX Series

Non-Powered
Powered, Analog
RHAON Empowered
RHAON & Dante
RHAON & Dante Redundant

8" LF + 1" HF Two-way, Complex Conic Loudspeaker



• Complex Conic Horn

Consistent directivity, superior sonics and field rotatable.

• Surprising Power

90 Hz to 20 kHz response and 123 dB, peak SPL.

Build-to-Order Flexibility

Horn dispersion and rotation options, custom color and IP55 Weather Resistant finishes are available.

• Optional U-Bracket Mount

Allows easy horizontal mounting and aiming.

• Available SA625 Amplifier

SA625 amplifier offers high output, full protection limiting, analog, and optional AES and Dante inputs.

© 2019 Renkus-Heinz Inc. reserves the right to change any product specification without prior notification.

		TA/TX81 Specificatio	ons		
	TX81	TA81-A	TA81-RN	TA81-RD1 & RD	
connectors:	2 x Speakon [®] NL4 Four-place terminal strip, all paralleled	2 x XLR-3, In & Loop-out	2 x XLR-3, In & Loop-out, Analog and AES 2 x RJ45, primary & secondary		
ensitivity:	96 dB (1W/1m)	1.0 volt for rated output, analog			
Power Handling:	Passive: 125 W AES @ 16 ohms, Bi-amp: 125 W AES @ 16 ohms, LF 20 W AES @ 16 ohms, HF	See SA625 amplifier specs below			
Crossover Frequency:	2.2 kHz, passive, bi-amp selectable	2.2 kHz activ	e electronic		
Veight:	25	bs/11.3 kg			
requency Response:	90 Hz to 20 kHz (+/- 3dB)				
lax. SPL:	123 dB (peak, whole space)				
Dispersion	120° horizontal x 60° vertical or 90° horizontal x 60° vertical, Rotatable Complex Conic Horn				
inclosure:	11 ply birch plywood				
Grille:	16 (16 GA powder-coated, plated steel			
ransducers:	Woo	Woofer: SSL8-20; High Frequency Driver: SSD1445-16; Replacement HF Diaphragm CD1445-16			
inish:	Blac	ck (RAL9010) or White (RAL9011) paint. Custom	color matching and IP55 WR Treatment optiona	L	
Mounting:		KM6 UMH points; 2 x M10 u-bracket nutplate. 0			
-		⁵ / ₁₆ " w x 21" h x 10- ¹ / ₂ " d		× ,	
Dimensions:		2 mm w x 533 mm h x 267 mm d			
		SA625 Amplifier Specific	ations		
	SA625-A	SA625-RN	SA625-RD1 (Ultimo)	SA625-RD (Brooklyn II)	
	URULU-A			2 x XLR-3, In & Loop-out, Analog and AE	
udio Connections:	2 x XLR-3, In & Loop-out, Analog	2 x XLR-3, In & Loop-out, Analog and AES	2 x XLR-3, In & Loop-out, Analog and AES 1 x RJ45 Dante Ethernet	2 x RJ45 Dante Primary & Secondary Ethernet	
_atency:	6.25 ms	6.25 ms	6.25 ms Analog & AES	6.25 ms Analog & AES	
			6.25 ms + Dante transport latency	6.25 ms + Dante transport latency	
Iser DSP:	None		helf, high and low pass filters, delay to 340 ms.		
oftware:	None	RHAON II	RHAON II and Dante Controller		
Max. Input Level:	+22 dBu, Analog	+22 dBu, Analog, 0 dBFS digital	+22 dBu, Analog, 0 dBFS digital	+22 dBu, Analog, 0 dBFS digital	
letwork Connections:	None	2 x RJ45, Looping Ethernet/RHAON	2 x RJ45, DANTE/Looping Ethernet/ RHAON (Note: Dante and RHAON share a single Ethernet network.)	2 x RJ45 Dante Primary & Secondary Ethernet/RHAON (Note: Dante and RHAO share a single or redundant Ethernet network.)	
Power Output:	LF= 250 watts, @ 16 ohms / HF = 125 watts @ 16 ohms. Multi-band peak and thermal limiting on both channels protects the drivers. Neutrik NL4 provides processed, loop-out to second TX81. (Looped-to loudspeaker must be in bi-amp mode.)				
Mains Voltage:	100-240 volts, 50/60 Hz auto-switching				
Power Consumption:		: 200 mW. 1/8 power: 120 W (onset of limiting) 1	1/3 power: 240 w (nard limiting)		
Power Connector:		ttrik powerCON TRUE-1		L L 000 5/00 0	
Temperature Limits		k.: 140° F/60° C, with no direct sun exposure; Mi d outputs comply with AES Standard 48-2005 o		warm below 32° F/0° C.	
	- 10-1/2" 10-5/11	5° → 267 mm → C = Approximate Center 01 TX DIM A = 5-1/4 in. (1		SA625-A Amplifier option	



Renkus-Heinz, Inc., 19201 Cook Street, Foothill Ranch, TA 92810-3501, USA Tel: +1 949-588-9997 • Fax: +1 949-588-9514 sales@renkus-heinz.com • www.renkus-heinz.com