

### Smart Switch Relay Mechanism

Product Code:  
**RM1440BH-W**

#### APP Installation

Visit [www.kasta.com.au](http://www.kasta.com.au) or your app store to download the free KASTA app.  
iOS: requires iOS 9.0 or later.  
Android: requires Android 4.4 or later.  
Devices must support Bluetooth 4.0



#### Important Safety Information

- This product must be installed by a licensed electrician in accordance with all the requirements of AS/NZS 3000 (current edition) and other relevant Standards and Regulations.
- Electricity MUST be disconnected prior to installation. Failure to do so may result in serious injury and or loss of life.
- Indoor use only. Not suitable for damp or explosive environments.
- Complies to Australian Standards AS/NZS 60950.1:2015, AS/NZS CISPR 15.
- No user serviceable parts inside.

### FEATURES

- Relay for switching a load on and off.
- Smart functions via phone/tablet with the app such as schedules, timers, scenes and groups.
- Push Button Control.
- Fits most Australian Standard wall mech apertures.
- Simple 3 wire connection-Active in, load out and neutral.
- Integral blue backlight that can be enabled/disabled after installation.
- Multi-way load switching possible using KASTA remote switches.

### FUNCTION SETUP

ON/OFF SWITCH	1 CLICK
Turns load on or off.	
DELAY TO OFF	3 CLICKS*
Load automatically turns off after set time.	
PAIRING MODE	6 CLICKS
Enter pairing mode for multi-way switching. Lights will pulse.	
BACKLIGHT ON/OFF	7 CLICKS
Disables or enables backlight on button.	
FACTORY RESET	9 CLICKS

Restores all settings back to factory.

\*If successful, light will pulse the number of times that the switch was clicked, indicating function.

### TECHNICAL SPECIFICATIONS

**Operating Temp:** -20°C to 40°C


**Supply:** 220-240V AC 50Hz

**Load:** 480W


**Thermal Derating:** 25°C to 40° (480W-100 W)

### CONNECTION DIAGRAM

#### ONE WAY SWITCHING



#### MULTI-WAY SWITCHING



REMOTE SWITCH



REMOTE SWITCH

\*Maximum 8 Remote Switches